



Hewlett Packard
Enterprise

Red Hat Enterprise Linux 8.3

Supplement for Service Pack for ProLiant 2020.09.0 Gen10

Release Notes

December 2020

Legal and notice information

© Copyright 2020 Hewlett Packard Enterprise Development LP

DocumentHistory:

Released	Description
December 2020	Final Version
December 2020	SPP version updated from 2020.03.0 to 2020.03.2 and 2019.12.0 to 2019.12.2 which got released to address BootHole vulnerability issue fix in the supported versions of SPP table.

Table of Contents

Overview	4
Update recommendation	4
Alignment	4
Summary of Changes	4
Important Notes	4
Release Summary	5
Prerequisites	5
Running SUM on Linux	5
Deployment Instructions	6
Component Release Notes	7

Overview

A Service Pack for ProLiant (SPP) Supplement is a bundle containing software and/or firmware components with SUM as the deployment tool. It may include support for a new operating system update or functionality that is not included in the SPP but works with the components in the SPP. The software and firmware included in the Supplement will provide support for functionality that is required outside a normal SPP release cycle. Supplements allow HPE to deliver support when it is needed so customers do not have to wait on a full SPP's availability.

Each SPP Supplement's version number will match the version of its corresponding SPP. Supplement Release Notes will be available and will include information on the components in the bundle. If the Supplement's contents include Linux components, the components will also be available on the Linux Software Delivery Repository (SDR).

Once released, the functionality of the SPP Supplement contents is included in the next available SPP.

Beginning with 2020.03.0, there is an additional Gen10 production Supplement SPP release.

Hot Fixes associated with an SPP may work with an SPP Supplement. Please review the Hot Fix to verify if it has support for the operating system that is supported in the Supplement. For more information on SPP Hot Fixes, please see the SPP Release Notes located on the [SPP Information Library page](#).

This is the Red Hat Enterprise Linux (RHEL) 8.3 Supplement for Gen10 Service Pack for ProLiant 2020.09.0.

For more information on which servers are supported with RHEL 8.3, please visit our OS Support Site at: <https://www.hpe.com/servers/ossupport>.

Product Name	Comment
RHEL8.3 Supplement for Gen10 SPP version 2020.09.0	Bundle containing software components Filename: gen10sup spp-2020.09.rhel8.3.en.tar.gz

Update recommendation

Optional - Users should update to this version if their system is affected by one of the documented fixes or if there is a desire to utilize any of the enhanced functionality provided by this version.

Alignment

Gen10 Service Pack for ProLiant 2020.09.0

Summary of Changes

Important Notes

When the terms, Supplement, Service Pack for ProLiant or SPP are used throughout this document, they refer to all of the deliverables in the Table in the Overview Section unless explicitly stated.

⚠ Before deploying any components to a system, be sure that a recent backup of the system is available in the event the deployment procedure fails.

Release Summary

The summary of Red Hat Enterprise Linux (RHEL) 8.3 Supplement for Service Pack for ProLiant Gen10 release is:

Added support for Red Hat Enterprise Linux 8.3

This Supplement corresponds with Gen10only SPP 2020.09.0. Drivers either found in this SPP 2020.09.0 Gen10Only or delivered with the RHEL 8.3 distribution can be used. However, the drivers found in the initial release (SPP 2020.09.0 Gen10Only) may not contain all of the HPE value added features that are available in the Supplement. These features will be added in a future SPP release.

All components delivered in this Supplement to the Service Pack for ProLiant (SPP) are tested together and meet the dependencies of the other components in the Service Pack for ProLiant.

Systems using software and firmware components delivered with the following products should be able to easily migrate to the components in this supplement:

Product	Version
Service Pack for ProLiant	2020.09.0
	2020.03.2

Note: The users may see the “thawing” state in the systemd message console because the systemd doesn’t set the default value correctly, especially after a restart or reload services.

Prerequisites

Running SUM on Linux

⚠ Before deploying software updates on a target system, be sure that a recent backup of the target system is available in the event the deployment procedure fails.

To successfully deploy SUM on remote target systems based on a Linux operating system, the following must be available:

- libcrypt.so

- libcrypt.so.1
- /usr/lib/libqldsdm.so
- /usr/lib64/libqldsdm-x86_64.so
- /lib/cim/libqldsdm.so
- /usr/lib/libemsdm.so
- /usr/lib64/libemsdm.so
- /lib/cim/libemsdm.so
- /usr/lib/bfahbaapi.so
- /usr/lib64/bfahbaapi.so
- /lib/cim/bfahbaapi.so
- linux-vdso.so.1
- /lib64/libcrypt.so.1
- /lib64/libpthread.so.0
- /lib64/libz.so.1
- /lib64/libdl.so.2
- /lib64/librt.so.1
- /usr/lib64/libstdc++.so.6
- /lib64/libm.so.6
- /lib64/libgcc_s.so.1
- /lib64/libc.so.6
- /lib64/ld-linux-x86-64.so.2

Deployment Instructions

The Supplement is designed for use after the operating system is installed. This enables the updating of drivers, and the installation of HPE utilities (such as Health and iLO drivers), and agents (Server, NIC, and Storage).

Using the SPP Supplement and its corresponding SPP on a supported Linux operating system. Enables the choice of either standard Linux installation tools (YUM/Zypper) or HPE management tools (SUM/OneView) to do the following:

- Use the software and firmware provided in the Supplement and the SPP.
- Use the firmware provided in the SPP and get the software from the Software Delivery Repository at <https://downloads.linux.hpe.com/SDR>.
- Use the firmware and software utilities provided in the SPP and get the drivers from the operating system distro.

When appropriate for any given deployment, components can be combined into a single ISO using SUM custom baseline or applied as separate packages.

Note: Gen10 iLO 5 Linux and iLO 5 nodes only -to manage the iLO Repository, select the iLO Repository Options tab. (When running SUM in GUI mode).

To upload selected components to the iLO Repository and create an install set, select Save Components as an Install set on iLO Repository. SUM automatically creates a default name and description, but you can edit the name and description for the install set. You can use this install set to roll back the server components at a future time. The name and description are **limited to 63 characters**, and the only special characters allowed are - and _.

Component Release Notes

Release Notes for RHEL8.3 Supplement for Gen10 SPP, v2020.09.0

[Driver - Storage Controller](#)

[Software - Lights-Out Management](#)

[Software - System Management](#)

Driver - Storage Controller

[Top](#)

HPE ProLiant Gen10 and Gen10Plus Smart Array Controller (64-bit) Driver for Red Hat Enterprise Linux 8 (64-bit)

Version: 2.1.6-006 (Recommended)

Filename: kmod-smartpqi-2.1.6-006.rhel8u2.x86_64.compsig, kmod-smartpqi-2.1.6-006.rhel8u2.x86_64.rpm, kmod-smartpqi-2.1.6-006.rhel8u3.x86_64.compsig, kmod-smartpqi-2.1.6-006.rhel8u3.x86_64.rpm

Important Note!

-

Fixes

-

Enhancements

-

Supported Devices and Features

SUPPORTED KERNELS:

The kernels of Red Hat Enterprise Linux8 (64-bit) supported by this binary rpm are:
-default- Red Hat Enterprise Linux 8 Update 0 (64-bit).

Software - Lights-Out Management

[Top](#)

HPE Lights-Out Online Configuration Utility for Linux (AMD64/EM64T)

Version: 5.6.0-0 (**Optional**)

Filename: hponcfg-5.6.0-0.x86_64.compsig; hponcfg-5.6.0-0.x86_64.rpm

Prerequisites

This utility requires the following minimum firmware revisions:

- Integrated Lights-Out 3 firmware v1.00 or later
- Integrated Lights-Out 4 firmware v1.00 or later
- Integrated Lights-Out 5 firmware v1.20 or later

The management interface driver and management agents must be installed on the server.

For iLO 5, openssl v1.0.x or later is required in addition to above packages.

Customers who manually compile and install openssl or intentionally relocate /usr/bin/openssl, need to set PATH environment variable to direct HPONCFG to the right/intended openssl.

Fixes

Fixed an issue where HPONCFG was not able to detect openssl library when multiple 64-bit openssl installed.

Enhancements

Updated product name to HPE Lights-Out Online Configuration Utility for Linux (AMD64/EM64T).

Software - System Management

[Top](#)

Agentless Management Service (iLO 5) for Red Hat Enterprise Linux 8 Server

Version: 2.3.0 **(Optional)**

Filename: amsd-2.3.0-1443.35.rhel8.x86_64.compsig; amsd-2.3.0-1443.35.rhel8.x86_64.rpm

Prerequisites

- amsd only supported on HPE Gen10 Servers.
- amsd provides information to the iLO 5 service providing SNMP support.

Requirements:

- Minimum iLO 5 Firmware Version = 1.1
- Minimum supported OS Versions = Red Hat Enterprise Linux 7.3 Errata 3.10.0.514.6.1

Fixes

Fixed the following items:

- The ahslog service in the HPE Agentless Management Service (iLO 5)(amsd) for Linux may segfault during system startup. While this occurs, the user can see the "Failed to start Active Health Service Logger" message from the systemctl. Review Customer Advisory [a00099165en_us](#) for additional details.
- When customers set the kernel parameter to disable the ipv6 in RHEL, the memory usage of HPE Agentless Management Service (AMSD) is much more stable.
- Corrected the test trip cannot be generated with the test parameter in the HPE Agentless Management Service (AMSD).
- Addressed ahslog stability to allow service back when iLo restarts. Customers will no longer experience the service hang after the iLO reboot.
- Fiber options correctly delivers data in the reverse mode (SMA)

Enhancements

Enhancements included in this release:

- Support for the following new network controllers:
 - P10118-B21 HPE Ethernet 10/25Gb 2-port SFP28 QL41232HQCUCP3 Adapter
 - P22702-B21 HPE Ethernet 10/25Gb 2-port SFP28 QL41222HLCU Adapter
 - 874253-B21 HPE Ethernet 100Gb 1-port 842QSFP28 Adapter

HPE Smart Storage Administrator (HPE SSA) CLI for Linux 64-bit

Version: 4.21.7.0 **(Optional)**

Filename: ssacli-4.21-7.0.x86_64.compsig; ssacli-4.21-7.0.x86_64.rpm; ssacli-4.21-7.0.x86_64.txt

Important Note!

HPE SSA CLI will allow you to configure and manage your storage as before, but now with additional features, abilities, and supported devices. Existing ACUCLI scripts should only need to make minimal changes such as calling the appropriate binary or executable in order to maintain compatibility.

Fixes

ADU report does not capture Slotx log greater than 4GiB size if configured.

Enhancements

Added support for HPE Smart Array S100i SR Gen10 Plus SW RAID

HPE Smart Storage Administrator (HPE SSA) for Linux 64-bit

Version: 4.21.7.0 (**Optional**)

Filename: ssa-4.21-7.0.x86_64.compsig; ssa-4.21-7.0.x86_64.rpm; ssa-4.21-7.0.x86_64.txt

Important Note!

HPE SSA replaces the existing HP Array Configuration Utility, or ACU, with an updated design and will deliver new features and functionality for various Smart Storage initiatives as they come online. HPE Smart Array Advanced Pack 1.0 and 2.0 features are now part of the baseline features of HPE SSA, with the appropriate firmware.

HPE SSA will allow you to configure and manage your storage as before, but now with additional features, abilities, and supported devices. Existing ACU scripts should only need to make minimal changes such as calling the appropriate binary or executable in order to maintain compatibility.

Prerequisites

The HPE Smart Storage Administrator for Linux requires the HPE System Management Homepage software to be installed on the server. If the HPE System Management Homepage software is not already installed on your server, please download it from HPE.com and install it before installing the HPE Smart Storage Administrator for Linux.

IMPORTANT UPDATE: HPE SSA (GUI) for Linux can now be run without requiring the HPE System Management Homepage. HPE SSA now supports a Local Application Mode for Linux. The HPE System Management Homepage is still supported, but no longer required to run the HPE SSA GUI.

To invoke, enter the following at the command prompt:

```
ssa -local
```

The command will start HPE SSA in a new Firefox browser window. When the browser window is closed, HPE SSA will automatically stop. This is only valid for the loopback interface, and not visible to external network connections.

Fixes

ADU report does not capture Slotx log greater than 4GiB size if configured.

Enhancements

Added support for HPE Smart Array S100i SR Gen10 Plus SW RAID

HPE Smart Storage Administrator Diagnostic Utility (HPE SSADU) CLI for Linux 64-bit

Version: 4.21.7.0 (**Optional**)

Filename: ssaduccli-4.21-7.0.x86_64.compsig; ssaduccli-4.21-7.0.x86_64.rpm; ssaduccli-4.21-7.0.x86_64.txt

Important Note!

This stand alone version of the HPE Smart Storage Administrator's Diagnostic feature is available only in CLI form. For the GUI version of Diagnostic reports, please use HPE Smart Storage Administrator (HPE SSA).

Fixes

ADU report does not capture Slotx log greater than 4GiB size if configured.

Enhancements

Added support for HPE Smart Array S100i SR Gen10 Plus SW RAID
